



TELECOMPONENTS

TLDS/XX

Low Power -FM TRANSMITTER

50w - 100w - 300w - 500w



*TELECOMPONENTS
LOW POWER TRANSMITTERS
50w -100w - 300w - 500w*





PRODUCT DESCRIPTION

Available with RF nominal power of 50W, 100W, 300W, 500W, 1000W

The Low Power Series of FM Transmitter, ranging from 30W to 1.1 kW, features very compact dimensions associated with Telecomponents most innovative

technological characteristics. A reliable device, easy to be used and controlled, including the best performances in a small size.

The standard configuration includes various features, while others are available on request.



Also available in a redundant hot plug version starting from 2019

MAIN FEATURES

- Highest overall efficiency $\geq 73\%$
- Nominal RF power up to 50W, 100W, 300W, 500W, 1000W
- UAQ Ultimate Audio Quality
- High stereo performance typ. 60 dB
- Remote Control through mobile APP
- Web TCP/IP
- 6th LD-MOS generation VSWR 65:1
- Large LCD color display with touch panel
- Ac mains 90-260 VAC extend range with PFC
- CCIR & FCC compliant

OPTIONS

- DDS Direct Digital Synthesis
- AES/EBU Audio Input
- RDS/RBDS coder
- SNMP v2, V3 remote control
- OIRT and JPN version
- Audio Over IP
- GPS Telemetry
- SFN Reference
- Deep Tropicalization

- Deep Tropicalization

PRODUCT INNOVATION

The Low power series of FM Transmitter is provided with the best available technologies developed by Telecomponents Laboratories. Our innovative solutions are carefully designed in order to always guarantee efficiency, reliability and ease of use.


Maximized Efficiency System

MES is an intelligent system of automatic regulation of the power devices working point: efficiencies RF/AC up to 85% and reduction of air and electricity consumption.



Ultimate Audio Quality

UAQ is a sophisticated system that allows to obtain audio quality levels higher than industry standards and the current characteristics of digital modulations.



Intelligent Air Cooling System

ICS is a smart innovation that regulates the amount of cooling air according to the environmental conditions and the needs of the transmitter, reducing energy waste.




Evolution Touch

Quick and intuitive control of the Transmitter thanks to the full colour touch screen, an easy-to-use LCD display installed on the device front panel.




Software Energy Saving

Energy and time saving through RFE smart software, directly installed on the Transmitter: the innovative firmware ensuring easy control and high performance.




Full Audio Interface

All the basic audio features included in RFE Transmitters: L+R board, MPX audio and Stereo coder in order to obtain almost digital audio quality.




Mobile Remote Control

Complete and remote control of the Transmitter via mobile, web or GSM, monitoring every function in total comfort.



Liquid Cooling System AVAILABLE ON REQUEST

RFE innovative solution designed to improve the action of cooling the Transmitter by using liquids such as water, instead of the usual air system.



Direct Digital Synthesis AVAILABLE ON REQUEST

The innovation of the digital audio modulator, a smart technology able to further improve audio quality by producing digital sound.

GENERAL	Power Output	50w-100w-300w-500w adjustable from the front panel
	RF Output Impedance	50 ohm
	RF Output Connector	N or 7/16"
	Monitor RF	BNC connector
	VSWR	1,5:1 WITH AUTOMATIC FOLDBACK
	Frequency Range	87.5 ÷ 108.00 MHz, on request 66 ÷ 74 MHz (OIRT) 76 ÷ 90 MHz (JPN) Programmable in 10kHz steps
	Frequency Stability	±1 ppm from -5 to 45°C
	Type of Modulation	Analog
	Off Lock Attenuation	≥ -80 dBc
	Modulation Capability	±150 KHz
	Limiter built in	
	Power Good Detector	adjustable from 20÷90% of the power
	Audio Presence Detector	adjustable time from front panel
	External AGC	Automatic, with fine ADJ back panel
	Modulation Mode	Mono, Stereo, Multiplex, SCA, RDS, Aux
	Preemphasis	Flat/50/75µs selectable from front panel
	Asynchronous AM S/N Ratio	-70 dB
	Synchronous AM S/N Ratio	-60 dB
	RF Harmonics	Exceeds EBU/CCIR/FCC requirements
	RF Spurious	Exceeds EBU/CCIR/FCC requirements
MONO OPERATION	Audio Input Impedance	600 ohm - 10 Kohm balanced
	Audio Input Level	-6 to +12 dBm
	Input Connector	XLR female
	Audio Frequency Response	±0.1 dB, 20 Hz to 15 KHz
	Total Harmonic Distortion + Noise	0.1% @ 400 Hz
	Intermodulation Distortion	0.1%, 1 KHz/1.3 KHz, 1:1 ratio
	Transient Intermodulation Distortion	0.1% 2.96KHz square wave and 14 KHz sine wave
	Distortion	0.1% 2.96KHz square wave and 14 KHz sine wave
	FM S/N Ratio	-80 dB ±75 KHz dev.
	STEREO OPERATION	Audio Input Impedance
Audio Input Level		-6 to +12 dBm
Input Connector		XLR female
Audio Frequency Response		±0.1 dB, 20 Hz to 15 KHz
Total Harmonic Distortion + Noise		0.1% @ 400 Hz
Intermodulation Distortion		0.1%, 1 KHz/1.3 KHz, 1:1 ratio
Transient Intermodulation Distortion		0.1% 2.96KHz square wave and 14 KHz sine wave
FM S/N Ratio		-80 dB below ±75 KHz dev.
Stereo Separation		@1kHz ≥ -60dB
Crosstalk attenuation		Main to Sub -70 dB 30 Hz to 15 KHz
38 KHz Suppression		≥ -85 dB
Pilot Frequency		19 KHz ± 1 Hz
Output Pilot		1 Vpp., BNC female

MULTIPLEX OPERATION	Composite Input Impedance	2 Kohm unbalanced
	Composite Input Level	-6 to +12 dBm
	Input Connector	BNC female
	Composite Amplitude Response	±0.1 dB, 30 Hz to 100 KHz
	Total Harmonic Distortion + Noise	0.1% @ 400 Hz
	Intermodulation Distortion	0.1%, 1 KHz/1.3 KHz, 1:1 ratio
	Transient Intermodulation Distortion	0.1% 2.96KHz square wave and 14 KHz sine wave
	FM S/N Ratio	-80 dB below ±75 KHz dev.
AES/EBU OPERATION	Input Connector	XLR female, optical TOS-LINK
	Data Format	S/PDF, AES/EBU, IEC958, EIAJCP340/1201
	D/A Converter	24 bit
	Sampling Frequency	from 32 to 96 KHz
SCA, RDS, AUX OPERATION	Input Impedance	≥ 2 Kohm
	Input Level	-6 to +12 dBm
	Frequency Response	±0.1 dB, 50 KHz to 100 KHz
	Input Connector	BNC female
AUXILIARY CONNECTIONS	RS485	DB9 connector back panel
	Telemetry Interface	connector DB25 back panel
	LAN	RJ45 connector back panel
	MPX OUT	connector BNC back panel
OPTIONS		AES/EBU -SPDIF
		RDS/RBDS Programmable Coder via PC
		OIRT or JPN version
		SNMP v2-v3
		Audio Over IP
		DDS Direct Digital Synthesis
ELECTRICAL	AC Input Power	200-400 VAC 50/60 HZ 3phase+N
	AC Apparent Power Consumption	100VA=50W, 200VA=100W, 450VA=300W, 750VA=500W
	Cos Ø	> 0.98
	Cooling	Forced air or Liquid Cooling (optional)
	Acoustic noise	< -56 dBa @ 1 meter
	SFN Reference	
ENVIRONMENTAL	Operating temperature	-10°C to +50°C
	Max Operating Altitude	4500 mt
	Relative Humidity Range	0 to 90%
PHYSICAL DIMENSION	Mounting	Standard 19" chassis ³⁶ U rack
	Size	W x580mm Dx1050 Hx1690mm
	Weight	-6Kg(50-100w), 8kg(300-500W)